

REMARKS

In the Office Action mailed on July 29, 2003, the disclosure has been objected to based on a number of informalities. It is believed that all of these informalities have been addressed herein. Specifically, the Examiner's suggested amendments to the specification on page 1, line 10; page 21, line 2, and page 24, line 22 have been made. The specification has been amended to further clarify the disclosure that begins on page 27, line 11, and to further clarify the reference labels of FIGS. 5(a) and 5(b). Finally, the specification has been amended to include additional detailed description of FIGS. 7 and 8.

The July 29 Office Action also objected to the drawings in that they fail to show the "scattering defect" claimed in claim 36 (originally numbered as claim 37). That claim has been cancelled herein, with the result that the objection to the drawings should be removed. The July 29 Office Action further objected to the specification in that it failed to provide an antecedent basis for the "superconducting" recitation of claim 2. Claim 2 has been amended herein, and in its amended form is supported by the specification. Claim 2 was also rejected as indefinite under 35 U.S.C. §112. It is believed that claim 2 as amended is definite under §112, and that this rejection should be withdrawn.

Claim 43 (originally numbered as claim 44) was described as vague and indefinite based on its recitation of "the adiabatic absorption." Claim 43 has been amended herein (referenced as original claim 44) to delete "the." It is respectfully submitted that claim 43 as amended is definite to one knowledgeable in the art, and that its rejection should be removed.

Claims 1, 3, 4 and 5 have been rejected under 35 U.S.C. §102(a) as anticipated by the Smith et al. paper. The title of the paper is not provided in the Office Action, and two papers by Smith et al. were submitted in an IDS in this matter. The citations in the Office Action, however, make clear that the paper referred to is "A COMPOSITE MEDIUM WITH SIMULTANEOUSLY NEGATIVE PERMEABILITY AND PERMITTIVITY" by D. R. Smith, Willie J. Padilla, D.C. Vier, S.C. Nemat-Nasser, and S. Schultz. As submitted in the

IDS filed on Nov. 13, 2001, this paper was identified as having a "Pre-print date" of January 2000. It has been determined that the actual publication date of this paper is May 2000. A copy of the published version of this paper has been enclosed herewith that shows its publication date of May 2000.

The present application claims priority under 35 U.S.C. §119(e) of U.S. Provisional Application 60/190,373 filed on March 17, 2000. Because the Smith et al. publication was published after the filing date of the provisional application, it cannot be 35 U.S.C. §102(a) prior art to the application. Accordingly, the anticipation rejection of claims 1, 3, 4 and 5 should be withdrawn.

Claims 23-26, 30, 31 and 37-39 have been rejected under 35 U.S.C. 103(a) as unpatentable over the Pendry reference in view of the Smith et al. paper. The Smith et al. paper, however, should be removed as a prior art reference since its publication date is after the filing date of the provisional application that the present application claims priority on. Accordingly, the obviousness rejection of claims 23-26, 30, 31 and 37-39 should be withdrawn.

Claims 2 and 43 have been indicated to be allowable if re-written or amended to overcome the §112 rejections discussed above. These claims have been amended herein to address the rejections, and are believed to be allowable in their amended form. Claims 6-16, 27-29, 32-37, 40 and 41 have been objected to as being dependent on a rejected base claim but are indicated to be otherwise allowable. This objection is believed to be moot, however, based on the belief that the underlying independent claims are allowable as discussed above. The Applicant reserves the right to present these objected-to claims in independent form in a subsequent amendment if necessary. Claim 42 (renumbered) has been allowed.

CONCLUSION

In the July 29 Office Action, several informalities in the specification were noted. These informalities are believed to be resolved as a result of amendments made herein. Several claims have been rejected as indefinite. These rejections are believed to have been overcome by the amendments made to the claims herein.

Claims 1, 3, 4, and 5 have been rejected as anticipated by the Smith et al. paper, and claims 23-26, 30, 31 and 37-39 have been rejected as obvious over the Pendry reference in combination with the Smith et al. paper. The present application claims priority on a provisional application that was filed before publication of the Smith et al. paper, however. As a result, the Smith et al. paper is not prior art to the present application, and these rejections should be withdrawn. Finally, several claims have been objected to as being dependent on a rejected claim but otherwise indicated to be allowable. Claim 42 has been allowed.

The Applicant believes that the present Amendment and Remarks have addressed all matters raised in the July 29 Office Action, and that all of the claims in their present format are in a condition suitable for allowance. Should the Examiner feel differently or have additional issues that require attention before the claims can be allowed, he is invited to contact the Applicant's undersigned attorney to discuss the same.

Respectfully submitted,

GREER, BURNS & CRAIN, LTD.

By: 

Thomas R. Fitzsimons
Reg. No. 40,607

300 South Wacker Drive
Suite 2500
Chicago, Illinois 60606
Telephone: 312.360.0080
Facsimile: 312.360.9315
Customer No. 24978

F:\Data\Wp60\0321\65200\Amendment B (9-30).doc

Composite Medium with Simultaneously Negative Permeability and Permittivity

D. R. Smith,* Willie J. Padilla, D. C. Vier, S. C. Nemat-Nasser, and S. Schultz

Department of Physics, University of California, San Diego, 9500 Gilman Drive, La Jolla, California 92093-0319

(Received 2 December 1999)

We demonstrate a composite medium, based on a periodic array of interspaced conducting nonmagnetic split ring resonators and continuous wires, that exhibits a frequency region in the microwave regime with simultaneously negative values of effective permeability $\mu_{\text{eff}}(\omega)$ and permittivity $\epsilon_{\text{eff}}(\omega)$. This structure forms a "left-handed" medium, for which it has been predicted that such phenomena as the Doppler effect, Cherenkov radiation, and even Snell's law are inverted. It is now possible through microwave experiments to test for these effects using this new metamaterial.

PACS numbers: 73.20.Mf, 41.20.Jb, 42.70.Qs

A periodic array of conducting elements can behave as an effective medium for electromagnetic scattering when the wavelength is much longer than both the element dimension and lattice spacing. What makes the resulting media special is that the effective permittivity $\epsilon_{\text{eff}}(\omega)$ and permeability $\mu_{\text{eff}}(\omega)$ can have values not observed in ordinary materials. An example medium is a three-dimensional array of intersecting thin straight wires, for which propagating modes follow a dispersion relation analogous to that of a neutral plasma. This medium was initially used to study microwave propagation through the ionosphere [1,2] [which exhibits a negative $\epsilon_{\text{eff}}(\omega)$ below the plasma frequency], and has since been carefully reexamined and found to have further striking electromagnetic properties, including longitudinal plasmon modes [3–5].

In recent work [6], Pendry *et al.* have extended the range of electromagnetic properties of effective media by introducing a periodic array of *nonmagnetic* conducting units whose dominant behavior can be interpreted as having an effective *magnetic* permeability. By making the constituent units resonant, the magnitude of $\mu_{\text{eff}}(\omega)$ is enhanced considerably, leading to large positive effective $\mu_{\text{eff}}(\omega)$ near the low frequency side of the resonance and, most strikingly, *negative* $\mu_{\text{eff}}(\omega)$ near the high frequency side of the resonance.

The concept of negative $\mu_{\text{eff}}(\omega)$ is of particular interest, not only because this is a regime not observed in ordinary materials, but also because such a medium can be combined with a negative $\epsilon_{\text{eff}}(\omega)$ to form a "left-handed" material (i.e., $\mathbf{E} \times \mathbf{H}$ lies along the direction of $-\mathbf{k}$ for propagating plane waves). In 1968, Veselago [7] theoretically investigated the electrodynamic consequences of a medium having both ϵ and μ negative and concluded that such a medium would have dramatically different propagation characteristics stemming from the sign change of the group velocity, including reversal of both the Doppler shift and Cherenkov radiation, anomalous refraction, and even reversal of radiation pressure to radiation tension. However, these effects could not be experimentally verified since, as Veselago pointed out, substances with $\mu < 0$ were not available. Negative $\mu_{\text{eff}}(\omega)$ has been shown to be possible when a polariton resonance exists in the permeability, such

as in the antiferromagnets [8,9] MnF_2 and FeF_2 , or certain insulating ferromagnets [10]. However, a negative permeability with low losses coexisting with a negative ϵ has not been demonstrated. The split ring resonator (SRR) medium recently introduced by Pendry *et al.* [6] has now given us the opportunity to make a material with negative permeability, from which a left-handed medium can be constructed, as we demonstrate below.

The system presented here is anisotropic to simplify the analysis; the isotropic medium, constructed by adding elements to increase the symmetry of a unit cell, will be presented elsewhere. A single copper SRR is shown in Fig. 1(inset) with the dimensions indicated. A time varying magnetic field applied parallel to the axis of the rings induces currents that, depending on the resonant properties of the unit, produce a magnetic field that may either oppose or enhance the incident field. The associated magnetic field pattern from the SRR is dipolar. By having splits in the rings, the SRR unit can be made resonant at




FIG. 1. Resonance curve of an actual copper split ring resonator (SRR). $c = 0.8$ mm, $d = 0.2$ mm, and $r = 1.5$ mm. The SRR has its resonance at about 4.845 GHz, and the quality factor has been measured to be $Q = f_0/\Delta f_{3\text{dB}} > 600$, consistent with numerical simulations.

wavelengths much larger than the diameter of the rings; that is, there is no half-wavelength requirement for resonance, as would be the case if the rings were closed. The purpose of the second split ring, inside and whose split is oriented opposite to the first, is to generate a large capacitance in the small gap region between the rings, lowering the resonant frequency considerably and concentrating the electric field. The individual SRR shown in Fig. 1(inset) has its resonance peak at 4.845 GHz. The corresponding resonance curve is shown in Fig. 1. Because the dimensions of the units are so much smaller than the free space wavelength, the radiative losses are small, and the Q 's are relatively large.

By combining the split ring resonators into a periodic medium such that there is strong (magnetic) coupling between the resonators, unique properties emerge from the composite. In particular, because these resonators respond to the incident magnetic field, the medium can be viewed as having an effective permeability, $\mu_{\text{eff}}(\omega)$. The general form of the permeability has been studied by Pendry *et al.* [6], where the following expression was derived:

$$\begin{aligned}\mu_{\text{eff}} &= 1 - \frac{\pi r^2/a^2}{1 - 3\ell/\pi^2\mu_0\omega^2 Cr^3 + i(2\ell\rho/\omega r\mu_0)} \\ &= 1 - \frac{F\omega^2}{\omega^2 - \omega_0^2 + i\omega\Gamma}\end{aligned}\quad (1)$$

Here ρ is the resistance per unit length of the rings measured around the circumference, ω is the frequency of incident radiation, ℓ is the distance between layers, a is the lattice parameter, r is defined in Fig. 1, F is the fractional area of the unit cell occupied by the interior of the split ring, Γ is the dissipation factor, and C is the capacitance associated with the gaps between the rings. The expressions for ω_0 and Γ can be found by comparing the terms in Eq. (1).

While the expression for the capacitance of the SRR may be complicated in the actual structure, the general form of the resonant permeability shown in Eq. (1) leads to a generic dispersion curve, such as that shown in Fig. 2(a). There is a region of propagation from zero frequency up to a lower band edge, followed by a gap, and then an upper passband. We note, however, that there is a symmetry between the dielectric and permeability functions in the dispersion relation $\omega = ck/\sqrt{\epsilon(\omega)\mu(\omega)}$, where c is the velocity of light in vacuum. The gap corresponds to a region where either $\epsilon_{\text{eff}}(\omega)$ or $\mu_{\text{eff}}(\omega)$ is negative. If we assume that there is a resonance in $\mu_{\text{eff}}(\omega)$ as suggested by Eq. (1) and that $\epsilon_{\text{eff}}(\omega)$ is positive and slowly varying, the presence of a gap in the dispersion relation implies a region of negative $\mu_{\text{eff}}(\omega)$. One cannot uniquely determine via only a simple measurement, or even the measurement of the dispersion relation itself, whether the gap is due to a




FIG. 2. (a) Dispersion curve for the parallel polarization H_{\parallel} . The lines with the solid circles correspond to the split ring resonators only. The inset shows the orientation of the split ring with respect to the incident radiation. The horizontal axis is the phase advance per unit cell, or kd , where k is the wave number. (b) Dispersion curve for the perpendicular polarization H_{\perp} . The lines with the solid circles correspond to the split ring resonators only. The inset shows the orientation of the split ring with respect to the incident radiation. (c) Expanded view of the dispersion curve shown in (a). The dashed line corresponds to the split ring resonators with wires placed uniformly between split rings. (d) Expanded view of the dispersion curve shown in (b). The dashed line corresponds to the split ring resonators with wires placed uniformly between split rings. The insets to (c) and (d) show the orientations of the split rings with respect to the wires.

resonance in the $\epsilon_{\text{eff}}(\omega)$ with constant $\mu_{\text{eff}}(\omega)$ or due to a resonance in $\mu_{\text{eff}}(\omega)$ with constant $\epsilon_{\text{eff}}(\omega)$, which we have indicated is the case. We discuss below the method we use to demonstrate that there is a region of negative $\mu_{\text{eff}}(\omega)$.

Using MAFIA [11], a commercial electromagnetic mode solver, dispersion curves were generated for the periodic infinite metallic structure consisting of the split ring resonators. There are two incident polarizations of interest: magnetic field polarized along the split ring axes [H_{\parallel} , Fig. 2(a), inset], and perpendicular to the split ring axes [H_{\perp} , Fig. 2(b), inset]. In both cases, the electric field is in the plane of the rings. As shown by the curves in Figs. 2(a) and 2(b), a band gap is found in either case, although we will show that we can interpret the H_{\parallel} gap of Fig. 2(a) as being due to negative $\mu_{\text{eff}}(\omega)$ and the H_{\perp} gap of Fig. 2(b) as being due to negative $\epsilon_{\text{eff}}(\omega)$. The negative permeability region for the H_{\parallel} modes begins at 4.2 GHz and ends at 4.6 GHz, spanning a band of about 400 MHz. Not evident from the figure, but consistent with the model indicated in Eq. (1), $\mu_{\text{eff}}(\omega)$ switches to a large negative value at the lower band edge, decreasing in magnitude (but still negative) for increasing frequency through the gap. At the upper band edge, $\mu_{\text{eff}}(\omega) = 0$, and a longitudinal mode exists (not shown), identified as the magnetic plasmon mode by Pendry *et al.* [6]. For the dielectric gap shown in Fig. 2(b), the same behavior is observed, but with the roles of $\epsilon_{\text{eff}}(\omega)$ and $\mu_{\text{eff}}(\omega)$ reversed.

Short of performing an intricate reflection and transmission measurement to fit the material constants, there is no simple means to deduce whether the split ring medium is responding electrically or magnetically. We can, however, use a physical approach and alter the dielectric function of the surrounding medium, creating scattering properties that can distinguish whether the band gaps are due to either the $\mu_{\text{eff}}(\omega)$ or $\epsilon_{\text{eff}}(\omega)$ of the SRR being negative.

In a 2D medium composed of periodically placed conducting straight wires, there is a single gap in propagation up to a cutoff frequency, ω_p , for modes with the electric field polarized along the axis of the wires [1–5]. This onset of propagation has been identified with an effective plasma frequency dependent on the wire radius and spacing, with the effective dielectric function following the form $\epsilon_{\text{eff}}(\omega) = 1 - \omega_p^2/\omega^2$. A reduction in ω_p can be achieved by restricting the current density to the thin wires, which also increases the self-inductance per unit length, L [3–5]. When the conductivity of the wires is large, the plasma frequency has been shown to have the general form $\omega_p = (d^2 L \epsilon_0)^{-1/2}$, and thin wire structures can easily be made to have ω_p at microwave or lower frequencies. Combining the SRR medium having a frequency band gap due to a negative permeability with a thin wire medium produces a resultant left-handed material in the region where both $\mu_{\text{eff}}(\omega)$ and $\epsilon_{\text{eff}}(\omega)$ have negative values.

Numerical simulations were carried out in which parallel wires of radius 0.8 mm were added in between the split rings, in a direction parallel to the incident electric field as shown in the inset of Fig. 2(c). The results of these simu-

lations are shown as dashed lines in Figs. 2(c) and 2(d). For the wires alone, a gap extends from zero frequency to ω_p , at 13 GHz. When wires are added symmetrically between the split rings, for the H_{\parallel} case a passband occurs within the previously forbidden band of the split ring dispersion curves of Fig. 2(a). *That this passband [the dashed line in Fig. 2(c)] occurs within a previously forbidden region indicates that the negative $\epsilon_{\text{eff}}(\omega)$ for this region has combined with the negative $\mu_{\text{eff}}(\omega)$ to allow propagation, as predicted.*

By combining the ideal frequency dependence for the wire medium [3] with Eq. (1) for the permeability of split rings, we can derive the following expression for the dispersion relation of the combined medium:

$$k^2 = \frac{(\omega^2 - \omega_p^2)}{c^2} \frac{(\omega^2 - \omega_b^2)}{(\omega^2 - \omega_0^2)}. \quad (2)$$

This equation shows that the range of the propagation band (k real) extends from ω_0 to $\omega_b = \omega_0/\sqrt{1 - F}$. This was formerly the region of the gap of the SRR structure in the absence of the wires. Note that the dispersion relation leads to a band with negative group velocity everywhere, and a bandwidth that is independent of the plasma frequency (provided $\omega_p > \omega_b$).

The behavior of the magnetic gap can be contrasted with that occurring for the H_{\perp} case, which we have identified as a dielectric gap. Because H is parallel to the plane of the SRR, we assume magnetic effects are small, and that $\mu_{\text{eff}}(\omega)$ is small, positive, and slowly varying. As shown in Fig. 2(d), a passband again occurs, but now outside of the forbidden region, and within a narrow range that ends abruptly at the band edge of the lowest propagation band. The passband in this case occurs where the effective dielectric function of the split rings exceeds the negative dielectric function of the wire medium. As the dispersion curves calculated do not include losses, there will always be a range of passband frequencies, however narrow, when the resonant dielectric medium of split rings is combined with the negative dielectric medium of wires. Once again, we can describe the behavior of the dielectric gap by an approximate dispersion relation,

$$k^2 \approx \frac{(\omega^2 - \omega_p^2)}{c^2} \frac{(\omega^2 - \omega_f^2)}{(\omega^2 - \omega_0^2)}, \quad (3)$$

where $\omega_f^2 = \omega_0^2 \omega_p^2 / (\omega_0^2 + \omega_p^2)$. In deriving Eq. (3), we have neglected the difference between ω_0 and ω_b , as ω_b does not play an essential role here, and assumed $\omega_p \gg \omega_0$. The propagation band in this case extends from ω_f to ω_0 , with a bandwidth strongly dependent on the plasma frequency. As the plasma frequency is lowered, the lower edge of the propagation band lowers, increasing the overall bandwidth. The group velocity of this band is always positive. Both Eqs. (2) and (3) neglect material losses (i.e., $\Gamma = 0$). The contrast between the two propagation bands in the H_{\parallel} and H_{\perp} cases illustrates the difference between the magnetic and dielectric responses of the split ring medium.




FIG. 3. A transmission experiment for the case of H_{\parallel} . The upper curve (solid line) is that of the SRR array with lattice parameter $a = 8.0$ mm. By adding wires uniformly between split rings, a passband occurs where μ and ϵ are both negative (dashed curve). The transmitted power of the wires alone is coincident with that of the instrumental noise floor (-52 dB).

The SRRs such as that shown in Fig. 1(inset) were fabricated using a commercially available printed circuit board. In order to test the results of the simulations, square arrays of SRRs were constructed with a lattice spacing of 8.0 mm between elements. The resonant mode of an individual element resembles a magnetic dipole, with electric fields strongly confined to the gap region between the rings, and the magnetic field circulating around the rings as in a wire loop. As the magnetic flux generated by the SRR is required to return within the unit cell, the fractional area F is the critical parameter for the enhancement of the permeability.

Microwave scattering experiments were performed on the fabricated SRR medium, and the combined SRR/metal wire medium. In order to ease the required size of the structure, we utilized a two-dimensional microwave scattering chamber, discussed previously in detail [12]. The scattering chamber is made out of aluminum, with a grid pattern of holes in the top plate to allow source and probe antenna coupling. Microwave absorber material placed around the periphery of the chamber minimized reflection back into the scattering region.

For the H_{\parallel} polarization we constructed 17 rows of split rings in the H direction (eight elements deep in the propagation direction), oriented as in Fig. 2(a), inset. Figure 3 shows the results of transmission experiments on split rings alone (solid curve), and split rings with wires placed uniformly between (dashed curve). The square array of metal

wires alone had a plasma frequency of 12 GHz; the region of negative ϵ below this frequency attenuated the transmitted power to below the noise floor of the microwave detector (-52 dBm). When split rings were added to the wire array, a passband occurred, consistent with the propagation region indicated by the simulation [Fig. 2(c)].

We have demonstrated both by numerical simulation and experiment that an effective medium of only conducting elements responds predominantly to the magnetic field of incident electromagnetic fields. Remarkably, there is a band of frequencies for which $\mu_{\text{eff}}(\omega)$ can be negative, here manifested as a region of attenuation in scattering from a finite section of material. We have combined this material with a negative $\epsilon_{\text{eff}}(\omega)$ material to form a "left-handed" medium, forming a propagation band with negative group velocity where previously there was only attenuation. We are now in a position to further investigate the fascinating electrodynamic effects anticipated for such composite metamaterials.

The authors thank Professor John Pendry for introducing them to the special properties of the SRR and the effective negative $\mu(\omega)$ concept as well as to helpful unpublished results and discussions. They also thank Mike Wiltshire of G. E. C. Marconi for supportive comments and discussion. This work was supported by the NSF (Contracts No. NSF-DMR-96-23949 and No. NSF-DMR-97-24535) and the DOE (Contract No. DOE-DE-FG-03-93ER40793).

*To whom all correspondence should be addressed.

Electronic address: drs@sdss.ucsd.edu

- [1] R. N. Bracewell, *Wireless Engineer* (Hiff & Sons Ltd., London, 1954), p. 320.
- [2] W. Rotman, IRE Trans. Antennas Propag. **AP10**, 82 (1962).
- [3] J. B. Pendry, A. J. Holden, W. J. Stewart, and I. Youngs, Phys. Rev. Lett. **76**, 4773 (1996).
- [4] J. B. Pendry, A. J. Holden, D. J. Robbins, and W. J. Stewart, J. Phys. Condens. Matter **10**, 4785 (1998).
- [5] D. R. Smith, D. C. Vier, Willie Padilla, Syrus C. Nemat-Nasser, and S. Schultz, Appl. Phys. Lett. **75**, 1425 (1999).
- [6] J. B. Pendry, A. J. Holden, D. J. Robbins, and W. J. Stewart, IEEE Trans. Microwave Theory Tech. **47**, 2075 (1999).
- [7] V. G. Veselago, Sov. Phys. USPEKHI **10**, 509 (1968).
- [8] D. L. Mills and E. Burstein, Rep. Prog. Phys. **37**, 817 (1974).
- [9] R. E. Camley and D. L. Mills, Phys. Rev. B **26**, 1280 (1982).
- [10] A. Hartstein, E. Burstein, A. A. Maradudin, R. Brewer, and R. F. Wallis, J. Phys. C **6**, 1266 (1973).
- [11] The MAFIA Collaboration, Release 4.0, F. Ebeling *et al.*, MAFIA User Guide, 1996.
- [12] D. R. Smith, R. Dalichaouch, N. Kroll, S. Schultz, S. L. McCall, and P. M. Platzman, J. Opt. Soc. Am. B **10**, 314 (1993).